Specifications / Model Name	**Acer X1260**
EMI/Safety Model No.	DNX0708
Projection System	DLP™
Resolution	Native XGA (1,024 x 768) Maximum SXGA+ (1,400 x 1,050), WXGA+ (1,440 x 900)
Computer Compatibility	IBM PC and Compatibles, Apple Macintosh, iMac, and VESA Standards WXGA+ (1,440 x 900), WXGA (1,280 x 800, 1,280 x 768), SXGA+ (1,400 x 1,050), SXGA (1,280 x 1,024), XGA (1,024 x 768), SVGA (800 x 600), VGA (640 x 480)
Video Compatibility	NTSC (3.58/4.43), PAL (B/D/G/H/I/M/N), SECAM (B/D/G/K/K1/L), HDTV (720p, 1080i), EDTV (480p, 576p), SDTV (480i, 576i)
Aspect Ratio	4:3 (Native), 16:9
Contrast Ratio	2000:1
Displayable Colors	16.7 Million Colors
Brightness	2,000 ANSI Lumens
Projection Lens	F = 2.41 ~ 2.55, f = 21.79mm ~ 23.99mm 1:1.1 Manual Zoom and Manual Focus
Projection Screen Size (Diagonal)	23" (58cm) ~ 300" (762cm)
Projection Distance	3.3' (1.0m) ~ 39.0' (11.9m)
Throw Ratio	50"@2m (1.95 ~ 2.15:1)
Horizontal Scan Rate	31 ~ 80k Hz
Vertical Refresh Scan Rate	50 - 85 Hz
Lamp Type	160 W user replaceable P-VIP lamp
Lamp Life	4,000 Hours
Keystone Correction	+/-40 Degrees (Vertical)
Projection Mode	Front, Rear, Front-Ceiling, Rear-Ceiling
Ceiling Mounting Capability	Yes
Audio	One Internal Speaker with 2 watts Output
Weight	5 lbs (2.3Kg)
Dimensions	267 x 187 x 80 mm (10.5" x 7.4" x 3.1")
Remote Control	IR remote control
Digital Zoom	2X

Downloaded from www.Manualslib.com manuals search engine

PIP	N/A
Wireless	N/A
Power Supply	AC input 100~240V auto-switching power supply
Power Consumption	255 Watts (Operation), <8 Watts (Standby)
Operating Temperature	5°C ~ 35°C / 41°F ~ 95°F
Noise Level	33 dBA
Uniformity	85%
Input Interface	Analog RGB/Component Video (D-sub) x 1
	Composite Video (RCA) x 1
	S-Video (Mini DIN) x1
	PC Audio (Stereo mini jack) x 1
Output Interface	Analog RGB (D-sub) x 1
Control Interface	USB (Type B) x 1
	RS232 (Mini DIN) x 1
Network Interface	
Standard Accessories	AC power cord
	VGA cable
	Composite video cable
	Remote control
	Battery for remote control
	Lens cap
	User's guide (CD-ROM)
	Quick start guide
	Security card

Downloaded from www.Manualslib.com manuals search engine